



Electronics Corporation



S2M-C

1/4 Watt

Input: Stereo Unbalanced Line

Output: Mono Unbalanced Line

Stereo Unbalanced Line Input

This is a stereo unbalanced 10K Ohms auxiliary line input. The connector is a stereo 3.5mm phono jack. This input is ideal for stereo computer line outputs, iPods, MP3 players, tape decks, tuners or other stereo unbalanced auxiliary level inputs. Tip signal "A", ring signal "B", sleeve ground.

Mono Unbalanced Line Output

This output is designed to supply signal to any mono unbalanced auxiliary level input like an amplifier, system monitor, mixer, etc. the output connector is a mono 3.5mm phono jack. Tip signal, ring/sleeve ground.

RoHS Compliant

Input Maximum Voltage: 5Vrms

Input: Stereo unbalanced 10K Ohms line level

Output: Mono unbalanced 10K Ohms line level

Frequency Response: 20~20K Hz., <1dBu

THD+Noise: <0.05% @ 1K Hz.

Mounting: Surface Mounted

Weight: 0.5 lbs.

Dimensions: 4.5" (L) x 2.5" (W) x 1.3" (H)

www.edcorusa.com

EDCOR Electronics Corporation

7130 National Parks Highway

Carlsbad, NM 88220

U.S.A.

(575) 887-6790

